DeepBluevet Sensor



Travel time, O/D matrices, incident detection, Online web based applications

Bluetooth, Wi-Fi, GPS, 3G, Dual-SIM, Ethernet, Multi-color LED, GPIO, RTC Battery, Non-volatile memory

Field proven, easy set-up and configuration, multi-lane, side-fire, Wireless device detection, tracking

Cost effective, Low power, Self-diagnostics, Autonomous, Reliable and secure transmission

ALL-IN-ONE
INTERNAL BLUETOOTH &
ANTENNAS V2t-PLATFORM

With our dedication to continuous development the specifications are subject to change. To verify the current information please visit www.deepbluesensor.com

DeepBlue V2t Sensor

Real Time Segment data

Click on a segment in order to display its information

Segment length:

POWER SUPPLY

12 to 48 VDC Min 1.22 W (configuration dependent) PoE (Power over Ethernet)

CPU & MEMORY

ARM 9 Processor 128 MB RAM / Flash Micro SD storage

COMMUNICATIONS

Ethernet
Optional 3G/CDMA Worldwide
Dual SIM-Card slot
Remote Sensor Access
Optional General Purpose IO

OPERATIONS

Linux based OS LED for operations diagnostics

ENVIRONMENTAL

-40°C to +80°C IP65 housing

Shock/vibration: NEMA TS2-2003

Heavy traffic if speed is below: Free-flowing traffic if speed is above: Average speed in segment: Average travel time: Oh 7 m 33 s Sample Size: Detected Devices: 10 Time interval: Show OD Matrix Show History Speed [kmih] 58.51 * Scans 2.23 * Probes 50 * Detected Devices 332 | 09-01-2014 11:45 | 4.11 80 1.03 20 12 pm 2 pm 4 pm 6 pm 8 pm 10 pm Thu Jan 9 4 am 6 am 8 am 10 am

[8] Av. Narcisa de Jesús Sector Sauces->Puente Unidad Nacional (Puntilla-Gouil)

DIMENSIONS & WEIGHT

H x W x L 200 mm x 148 mm x 62 mm 0.66 kg (1,035 kgincluding stainless steel brackets)

BLUETOOTH

internal antenna 65° angle Detects all standard Bluetooth® versions -102dB receive sensitivity

WI-FI

Optional Wi-Fi detection

REGULATORY

RoHS Compliant CE, FCC certified



With our dedication to continuous development the specifications are subject to change. To verify the current information please visit www.deepbluesensor.com